


G+H Electrical Accessories

Technical Datasheet



Description: Monarch Antique Brass Cooker Switch with Socket

Part Number: MAB329



Information

Plate Dimensions (mm)	154 (W) x 94 (H) x 8 (D)
Insert Material	Polycarbonate
Earth Strap	Mild Steel
Operating Voltage(AC)	250V @ 50Hz
Termination Type	Screw
Warranty	10 years
Product Class 1	Must be earthed
Maintenance	Clean with a soft cloth only. Do not use a cleaning agent of any description.
Please Note	Do not use masking tape on this product.
Style	Stepped Profile with Rope edge
Plate Material	Solid Brass, Hand-finished, Lacquered
Switch Material	Metal
Required back box depth	47mm
Load Rating	45A
Switch type	Double pole
Terminal Capacity	4x 4.0mm ² ,3x 6.0mm ² , 1x 16.0mm ² (L&N) / 3x 2.5mm ² ,2x 4.0mm ² , 1x 6.0mm ² (EARTH)
Standards	BS EN 60669-1, BS 4177(sockets)
IP Rating	IP2XD